# NAG Library Function Document nag\_hier\_mixed\_init (g02jcc)

## 1 Purpose

nag\_hier\_mixed\_init (g02jcc) preprocesses a dataset prior to fitting a linear mixed effects regression model of the following form via either nag\_reml\_hier\_mixed\_regsn (g02jdc) or nag\_ml\_hier\_mixed\_regsn (g02jec).

# 2 Specification

```
#include <nag.h>
#include <nagg02.h>

void nag_hier_mixed_init (Nag_OrderType order, Integer n, Integer ncol,
    const double dat[], Integer pddat, const Integer levels[],
    const double y[], const double wt[], const Integer fixed[],
    Integer lfixed, Integer nrndm, const Integer rndm[], Integer lrndm,
    Integer *nff, Integer *nlsv, Integer *nrf, double rcomm[],
    Integer lrcomm, Integer icomm[], Integer licomm, NagError *fail)
```

# 3 Description

nag\_hier\_mixed\_init (g02jcc) must be called prior to fitting a linear mixed effects regression model with either nag reml hier mixed regsn (g02jdc) or nag ml hier mixed regsn (g02jec).

The model fitting functions nag\_reml\_hier\_mixed\_regsn (g02jdc) and nag\_ml\_hier\_mixed\_regsn (g02jec) fit a model of the following form:

$$y = X\beta + Z\nu + \epsilon$$

where y is a vector of n observations on the dependent variable,

X is an n by p design matrix of fixed independent variables,

 $\beta$  is a vector of p unknown fixed effects,

Z is an n by q design matrix of random independent variables,

 $\nu$  is a vector of length q of unknown random effects,

 $\epsilon$  is a vector of length n of unknown random errors,

and  $\nu$  and  $\epsilon$  are Normally distributed with expectation zero and variance/covariance matrix defined by

$$\operatorname{Var} \begin{bmatrix} \nu \\ \epsilon \end{bmatrix} = \begin{bmatrix} G & 0 \\ 0 & R \end{bmatrix}$$

where  $R = \sigma_R^2 I$ , I is the  $n \times n$  identity matrix and G is a diagonal matrix.

Case weights can be incorporated into the model by replacing X and Z with  $W_c^{1/2}X$  and  $W_c^{1/2}Z$  respectively where  $W_c$  is a diagonal weight matrix.

## 4 References

None.

# 5 Arguments

## 1: **order** – Nag OrderType

Input

On entry: the **order** argument specifies the two-dimensional storage scheme being used, i.e., row-major ordering or column-major ordering. C language defined storage is specified by **order** = Nag\_RowMajor. See Section 3.2.1.3 in the Essential Introduction for a more detailed explanation of the use of this argument.

Constraint: order = Nag\_RowMajor or Nag\_ColMajor.

2: **n** – Integer

On entry: n, the number of observations.

The effective number of observations, that is the number of observations with nonzero weight (see wt for more detail), must be greater than the number of fixed effects in the model (as returned in nff).

Constraint:  $\mathbf{n} > 1$ .

3: **ncol** – Integer *Input* 

On entry: the number of columns in the data matrix, dat.

Constraint:  $ncol \ge 0$ .

4: dat[dim] – const double

Input

Note: the dimension, dim, of the array dat must be at least

```
max(1, pddat \times ncol) when order = Nag\_ColMajor; max(1, n \times pddat) when order = Nag\_RowMajor.
```

Where DAT(i, j) appears in this document, it refers to the array element

```
\mathbf{dat}[(j-1) \times \mathbf{pddat} + i - 1] when \mathbf{order} = \text{Nag\_ColMajor}; \mathbf{dat}[(i-1) \times \mathbf{pddat} + j - 1] when \mathbf{order} = \text{Nag\_RowMajor}.
```

On entry: a matrix of data, with  $\mathbf{DAT}(i,j)$  holding the *i*th observation on the *j*th variable. The two design matrices X and Z are constructed from  $\mathbf{dat}$  and the information given in  $\mathbf{fixed}$  (for X) and  $\mathbf{rndm}$  (for Z).

*Constraint*: if  $levels[j-1] \neq 1, 1 \leq DAT(i,j) \leq levels[j-1]$ .

5: **pddat** – Integer Input

On entry: the stride separating row or column elements (depending on the value of **order**) in the array **dat**.

Constraints:

```
if order = Nag_ColMajor, pddat \geq n; if order = Nag_RowMajor, pddat \geq ncol.
```

6: **levels**[**ncol**] – const Integer

Input

On entry: levels [i-1] contains the number of levels associated with the ith variable held in dat.

If the *i*th variable is continuous or binary (i.e., only takes the values zero or one) then  $\mathbf{levels}[i-1]$  must be set to 1. Otherwise the *i*th variable is assumed to take an integer value between 1 and  $\mathbf{levels}[i-1]$ , (i.e., the *i*th variable is discrete with  $\mathbf{levels}[i-1]$  levels).

Constraint: levels $[i-1] \ge 1$ , for i = 1, 2, ..., ncol.

7:  $\mathbf{y}[\mathbf{n}]$  – const double

On entry: y, the vector of observations on the dependent variable.

g02jcc.2 Mark 24

## 8: $\mathbf{wt}[\mathbf{n}]$ – const double

Input

On entry: optionally, the weights to be used in the weighted regression.

If  $\mathbf{wt}[i-1] = 0.0$ , the *i*th observation is not included in the model, in which case the effective number of observations is the number of observations with nonzero weights.

If weights are not provided then wt must be set to the null pointer, i.e., (double \*)0, and the effective number of observations is n.

Constraint: if wt is not NULL, wt $[i-1] \ge 0.0$ , for i = 1, 2, ..., n.

#### 9: **fixed**[**lfixed**] – const Integer

Input

On entry: defines the structure of the fixed effects design matrix, X.

#### fixed[0]

The number of variables,  $N_F$ , to include as fixed effects (not including the intercept if present).

## fixed[1]

The fixed intercept flag which must contain 1 if a fixed intercept is to be included and 0 otherwise.

**fixed**
$$[2 + i - 1]$$

The column of **DAT** holding the *i*th fixed variable, for i = 1, 2, ..., fixed[0].

See Section 9.1 for more details on the construction of X.

Constraints:

```
fixed[0] \geq 0; fixed[1] = 0 or 1; 1 \leq \text{fixed}[2 + i - 1] \leq \text{ncol}, for i = 1, 2, ..., \text{fixed}[0].
```

## 10: **lfixed** – Integer

Input

On entry: length of the vector fixed.

Constraint: **lfixed**  $\geq 2 +$ **fixed**[0].

## 11: **nrndm** – Integer

Input

On entry: the second dimension of the random effects design matrix RNDM.

Constraint: nrndm > 0.

#### 12: $\mathbf{rndm}[\mathbf{lrndm} \times \mathbf{nrndm}] - \mathbf{const} \ \mathbf{Integer}$

Input

**Note**: where RNDM(i, j) appears in this document, it refers to the array element

```
\mathbf{rndm}[(j-1) \times \mathbf{lrndm} + i - 1] when \mathbf{order} = \mathbf{Nag}_ColMajor; \mathbf{rndm}[(i-1) \times \mathbf{nrndm} + j - 1] when \mathbf{order} = \mathbf{Nag}_RowMajor.
```

On entry:  $\mathbf{RNDM}(i,j)$  defines the structure of the random effects design matrix, Z. The bth column of  $\mathbf{RNDM}$  defines a block of columns in the design matrix Z.

#### $\mathbf{RNDM}(1,b)$

The number of variables,  $N_{R_b}$ , to include as random effects in the *b*th block (not including the random intercept if present).

#### RNDM(2, b)

The random intercept flag which must contain 1 if block b includes a random intercept and 0 otherwise.

# RNDM(2+i,b)

The column of **DAT** holding the *i*th random variable in the *b*th block, for i = 1, 2, ..., RNDM(1, b).

## **RNDM** $(3 + N_{R_b}, b)$

The number of subject variables,  $N_{S_b}$ , for the *b*th block. The subject variables define the nesting structure for this block.

## **RNDM** $(3 + N_{R_b} + i, b)$

The column of **DAT** holding the *i*th subject variable in the *b*th block, for  $i = 1, 2, ..., \text{RNDM}(3 + N_{R_b}, b)$ .

See Section 9.2 for more details on the construction of Z.

Constraints:

**RNDM** $(1, b) \ge 0$ ;

**RNDM**(2, b) = 0 or 1;

at least one random variable or random intercept must be specified in each block, i.e.,  $\mathbf{RNDM}(1,b) + \mathbf{RNDM}(2,b) > 0$ ;

the column identifiers associated with the random variables must be in the range 1 to **ncol**, i.e.,  $1 \le \text{RNDM}(2+i,b) \le \text{ncol}$ , for i = 1,2,...,RNDM(1,b);

**RNDM** $(3 + N_{R_b}, b) \ge 0;$ 

the column identifiers associated with the subject variables must be in the range 1 to **ncol**, i.e.,  $1 \le \text{RNDM}(3 + N_{R_b} + i, b) \le \text{ncol}$ , for  $i = 1, 2, ..., \text{RNDM}(3 + N_{R_b}, b)$ .

13: **Irndm** – Integer *Input* 

On entry: maximum number of entries in any column of RNDM.

Constraint:  $\operatorname{Irndm} \geq \max_{b} (3 + N_{R_b} + N_{S_b}).$ 

14: **nff** – Integer \*

On exit: p, the number of fixed effects estimated, i.e., the number of columns in the design matrix X.

15: **nlsv** – Integer \* Output

On exit: the number of levels for the overall subject variable (see Section 9.2 for a description of what this means). If there is no overall subject variable,  $\mathbf{nlsv} = 1$ .

16: **nrf** – Integer \* Output

On exit: the number of random effects estimated in each of the overall subject blocks. The number of columns in the design matrix Z is given by  $q = \mathbf{nrf} \times \mathbf{nlsv}$ .

17: **rcomm**[**lrcomm**] – double

Communication Array

On exit: communication array as required by the analysis functions nag\_reml\_hier\_mixed\_regsn (g02jdc) and nag\_ml\_hier\_mixed\_regsn (g02jec).

18: **lrcomm** – Integer

Input

On entry: the dimension of the array rcomm.

 $\textit{Constraint: } \textbf{lrcomm} \geq \textbf{nrf} \times \textbf{nlsv} + \textbf{nff} + \textbf{nff} \times \textbf{nlsv} + \textbf{nrf} \times \textbf{nlsv} + \textbf{nff} + 2.$ 

19: **icomm**[**licomm**] – Integer

Communication Array

On exit: if  $\mathbf{licomm} = 2$ ,  $\mathbf{icomm}[0]$  holds the minimum required value for  $\mathbf{licomm}$  and  $\mathbf{icomm}[1]$  holds the minimum required value for  $\mathbf{lrcomm}$ , otherwise  $\mathbf{icomm}$  is a communication array as required by the analysis functions  $\mathbf{nag\_reml\_hier\_mixed\_regsn}$  (g02jdc) and  $\mathbf{nag\_ml\_hier\_mixed\_regsn}$  (g02jec).

g02jcc.4 Mark 24

20: **licomm** – Integer

Input

On entry: the dimension of the array icomm.

Constraint: licomm = 2 or

 $\begin{array}{l} \textbf{licomm} \geq 34 + N_F \times (MFL+1) + \textbf{nrndm} \times MNR \times MRL + (LRNDM+2) \times \textbf{nrndm} + \\ \textbf{ncol} + LDID \times LB,. \end{array}$ 

where

$$MNR = \max_{b}(N_{R_b}),$$

$$MFL = \max(\mathbf{levels}[\mathbf{fixed}[2+i-1]-1]),$$

$$\mathrm{MRL} = \max_{b.i}(\mathbf{levels}[\mathbf{RNDM}(2+i,b)-1]),$$

$$LDID = \max_{b} N_{S_b},$$

$$LB = \mathbf{nff} + \mathbf{nrf} \times \mathbf{nlsv}$$
, and

$$LRNDM = \max_{b} (3 + N_{R_b} + N_{S_b})$$

21: **fail** – NagError \*

Input/Output

The NAG error argument (see Section 3.6 in the Essential Introduction).

# 6 Error Indicators and Warnings

## NE\_ALLOC\_FAIL

Dynamic memory allocation failed.

## NE\_BAD\_PARAM

On entry, argument  $\langle value \rangle$  had an illegal value.

## NE INT

```
On entry, lfixed = \langle value \rangle.
```

Constraint: **Ifixed**  $\geq \langle value \rangle$ .

On entry, **licomm** =  $\langle value \rangle$ .

Constraint: **licomm**  $\geq \langle value \rangle$ .

On entry, **Ircomm** =  $\langle value \rangle$ .

Constraint: **Ircomm**  $\geq \langle value \rangle$ .

On entry, **lrndm** =  $\langle value \rangle$ .

Constraint: **Irndm**  $\geq \langle value \rangle$ .

On entry,  $\mathbf{n} = \langle value \rangle$ .

Constraint:  $\mathbf{n} \geq 1$ .

On entry,  $\mathbf{ncol} = \langle value \rangle$ .

Constraint:  $\mathbf{ncol} \geq 0$ .

On entry,  $\mathbf{nrndm} = \langle value \rangle$ .

Constraint:  $\mathbf{nrndm} > 0$ .

## NE\_INT\_2

On entry,  $\mathbf{pddat} = \langle value \rangle$  and  $\mathbf{n} = \langle value \rangle$ .

Constraint:  $pddat \ge n$ .

On entry,  $\mathbf{pddat} = \langle value \rangle$  and  $\mathbf{ncol} = \langle value \rangle$ .

Constraint:  $pddat \ge ncol$ .

## **NE INT ARRAY**

On entry, index of fixed variable j is less than 1 or greater than **ncol**:  $j = \langle value \rangle$ , index  $= \langle value \rangle$  and **ncol**  $= \langle value \rangle$ .

On entry, index of random variable j in random statement i is less than 1 or greater than **ncol**:  $i = \langle value \rangle$ ,  $j = \langle value \rangle$ , index  $= \langle value \rangle$  and **ncol**  $= \langle value \rangle$ .

On entry, invalid value for fixed intercept flag: value =  $\langle value \rangle$ .

On entry, invalid value for random intercept flag for random statement i:  $i = \langle value \rangle$ , value  $= \langle value \rangle$ .

On entry,  $\mathbf{levels}[\langle value \rangle] = \langle value \rangle$ . Constraint:  $\mathbf{levels}[i-1] \geq 1$ .

On entry, must be at least one parameter, or an intercept in each random statement i:  $i = \langle value \rangle$ .

On entry, nesting variable j in random statement i has one level:  $j = \langle value \rangle$ ,  $i = \langle value \rangle$ .

On entry, number of fixed parameters, (value) is less than zero.

On entry, number of random parameters for random statement i is less than 0:  $i = \langle value \rangle$ , number of parameters  $= \langle value \rangle$ .

On entry, number of subject parameters for random statement i is less than 0:  $i = \langle value \rangle$ , number of parameters  $= \langle value \rangle$ .

### **NE INTERNAL ERROR**

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

## **NE REAL ARRAY**

On entry, no observations due to zero weights.

On entry, variable j of observation i is less than 1 or greater than  $\mathbf{levels}[j-1]$ :  $i = \langle value \rangle$ ,  $j = \langle value \rangle$ ,  $\mathbf{value} = \langle value \rangle$ ,  $\mathbf{levels}[j-1] = \langle value \rangle$ .

On entry,  $\mathbf{wt}[\langle value \rangle] = \langle value \rangle$ . Constraint:  $\mathbf{wt}[i-1] \ge 0.0$ .

## NE\_TOO\_MANY

On entry, more fixed factors than observations,  $\mathbf{n} = \langle value \rangle$ . Constraint:  $\mathbf{n} \geq \langle value \rangle$ .

## 7 Accuracy

Not applicable.

## 8 Parallelism and Performance

Not applicable.

## **9** Further Comments

## 9.1 Construction of the fixed effects design matrix, X

Let

 $N_F$  denote the number of fixed variables, that is **fixed**[0] =  $N_F$ ;

 $F_j$  denote the jth fixed variable, that is the vector of values held in the kth column of **DAT** when  $\mathbf{fixed}[2+j-1]=k$ ;

g02jcc.6 Mark 24

```
F_{ij} denote the ith element of F_j;
```

 $L(F_j)$  denote the number of levels for  $F_j$ , that is  $L(F_j) = \mathbf{levels}[\mathbf{fixed}[2+j-1]-1];$ 

 $D_v(F_j)$  denoted an indicator function that returns a vector of values whose ith element is 1 if  $F_{ij} = v$  and 0 otherwise.

The design matrix for the fixed effects, X, is constructed as follows:

```
set k to zero and the flag done_first to false; if a fixed intercept is included, that is \mathbf{fixed}[1] = 1, set the first column of X to a vector of 1s; set k = k + 1; set done_first to true;
```

loop over each fixed variable, so for each  $j = 1, 2, ..., N_F$ ,

if 
$$L(F_j) = 1$$
,  
set the  $k$ th column of  $X$  to be  $F_j$ ;  
set  $k = k + 1$ ;  
else

if done\_first is false then

```
set the L(F_j) columns, k to k + L(F_j) - 1, of X to D_v(F_j), for v = 1, 2, ..., L(F_j); set k = k + L(F_j); set done_first to true;
```

set the  $L(F_j)-1$  columns, k to  $k+L(F_j)-2$ , of X to  $D_v(F_j)$ , for  $v=2,3,\ldots,L(F_j)$ ;

set the  $L(F_j)-1$  columns, k to  $k+L(F_j)-2$ , of X to  $D_v(F_j)$ , for  $v=2,3,\ldots,L(F_j)$  set  $k=k+L(F_j)-1$ .

The number of columns in the design matrix, X, is therefore given by

$$p = 1 + \sum_{j=1}^{N_F} (\mathbf{levels}[\mathbf{fixed}[2+j-1]-1]-1).$$

This quantity is returned in **nff**.

In summary, nag\_hier\_mixed\_init (g02jcc) converts all non-binary categorical variables (i.e., where  $L(F_j) > 1$ ) to dummy variables. If a fixed intercept is included in the model then the first level of all such variables is dropped. If a fixed intercept is not included in the model then the first level of all such variables, other than the first, is dropped. The variables are added into the model in the order they are specified in **fixed**.

## 9.2 Construction of random effects design matrix, Z

Let

 $N_{R_b}$  denote the number of random variables in the bth random statement, that is  $N_{R_b} = \mathbf{RNDM}(1,b)$ ;

 $R_{jb}$  denote the jth random variable from the bth random statement, that is the vector of values held in the kth column of **DAT** when **RNDM**(2 + j, b) = k;

 $R_{ijb}$  denote the *i*th element of  $R_{jb}$ ;

 $L(R_{jb})$  denote the number of levels for  $R_{jb}$ , that is  $L(R_{jb}) = \mathbf{levels}[\mathbf{RNDM}(2+j,b)-1];$ 

 $D_v(R_{jb})$  denoted an indicator function that returns a vector of values whose *i*th element is 1 if  $R_{ijb} = v$  and 0 otherwise;

```
N_{S_h} denote the number of subject variables in the bth random statement, that is
  N_{S_b} = \text{RNDM}(3 + N_{R_b}, b);
   S_{jb} denote the jth subject variable from the bth random statement, that is the vector of values held in
  the kth column of DAT when RNDM(3 + N_{R_b} + j, b) = k;
   S_{ijb} denote the ith element of S_{jb};
  L(S_{jb}) denote the number of levels for S_{jb}, that is L(S_{jb}) = \mathbf{levels}[\mathbf{RNDM}(3 + N_{R_b} + j, b) - 1];
  I_b(s_1, s_2, \ldots, s_{N_{S_b}}) denoted an indicator function that returns a vector of values whose ith element is
   1 if S_{ijb} = s_j for all j = 1, 2, ..., N_{S_b} and 0 otherwise.
The design matrix for the random effects, Z, is constructed as follows:
  set k to zero:
  loop over each random statement, so for each b = 1, 2, \dots, nrndm,
     loop over each level of the last subject variable, so for each s_{N_{S_b}} = 1, 2, \dots, L(R_{N_{S_b}b}),
           loop over each level of the second subject variable, so for each s_2 = 1, 2, \dots, L(R_{2b}),
              loop over each level of the first subject variable, so for each s_1 = 1, 2, \dots, L(R_{1b}),
                 if a random intercept is included, that is \mathbf{RNDM}(2,b) = 1,
                    set the kth column of Z to I_b(s_1, s_2, \ldots, s_{N_{S_b}});
                    set k = k + 1;
                 loop over each random variable in the bth random statement, so for each
                 j = 1, 2, \ldots, N_{R_b}
                    if L(R_{ib}) = 1,
                       set the kth column of Z to R_{jb} \times I_b \left( s_1, s_2, \dots, s_{N_{S_b}} \right) where \times indicates an element-
                       wise multiplication between the two vectors, R_{jb} and I_b(...);
                       set k = k + 1;
                    else
                       set the L(R_{bj}) columns, k to k + L(R_{bj}), of Z to D_v(R_{jb}) \times I_b(s_1, s_2, \dots, s_{N_{S_b}}),
                       for v = 1, 2, ..., L(R_{ib}). As before, \times indicates an element-wise multiplication
                       between the two vectors, D_v(\ldots) and I_b(\ldots);
                       set k = k + L(R_{ib}).
```

In summary, each column of **RNDM** defines a block of consecutive columns in Z. nag\_hier\_mixed\_init (g02jcc) converts all non-binary categorical variables (i.e., where  $L(R_{jb})$  or  $L(S_{jb}) > 1$ ) to dummy variables. All random variables defined within a column of **RNDM** are nested within all subject variables defined in the same column of **RNDM**. In addition each of the subject variables are nested within each other, starting with the first (i.e., each of the  $R_{jb}$ ,  $j = 1, 2, \ldots, N_{R_b}$  are nested within  $S_{1b}$  which in turn is nested within  $S_{2b}$ , which in turn is nested within  $S_{3b}$ , etc.).

If the last subject variable in each column of **RNDM** are the same (i.e.,  $S_{N_{S_1}1} = S_{N_{S_2}2} = \ldots = S_{N_{S_b}b}$ ) then all random effects in the model are nested within this variable. In such instances the last subject variable ( $S_{N_{S_1}1}$ ) is called the overall subject variable. The fact that all of the random effects in the model are nested within the overall subject variable means that  $Z^TZ$  is block diagonal in structure. This fact can be utilised to improve the efficiency of the underlying computation and reduce the amount of

g02jcc.8 Mark 24

internal storage required. The number of levels in the overall subject variable is returned in  $\mathbf{nlsv} = L(S_{N_{S_1}1})$ .

If the last k subject variables in each column of **RNDM** are the same, for k > 1 then the overall subject variable is defined as the interaction of these k variables and

$$\mathbf{nlsv} = \prod_{j=N_{S_1}-k+1}^{N_{S_1}} L(S_{j1}).$$

If there is no overall subject variable then  $\mathbf{nlsv} = 1$ 

The number of columns in the design matrix Z is given by  $q = \mathbf{nrf} \times \mathbf{nlsv}$ .

# 9.3 The rndm argument

To illustrate some additional points about the **rndm** argument, we assume that we have a dataset with three discrete variables,  $V_1$ ,  $V_2$  and  $V_3$ , with 2,4 and 3 levels respectively, and that  $V_1$  is in the first column of **DAT**,  $V_2$  in the second and  $V_3$  the third. Also assume that we wish to fit a model containing  $V_1$  along with  $V_2$  nested within  $V_3$ , as random effects. In order to do this the **RNDM** matrix requires two columns:

$$\mathbf{RNDM} = \begin{pmatrix} 1 & 1 \\ 0 & 0 \\ 1 & 2 \\ 0 & 1 \\ 0 & 3 \end{pmatrix}$$

The first column, (1,0,1,0,0), indicates one random variable (**RNDM**(1,1)=1), no intercept (**RNDM**(2,1)=0), the random variable is in the first column of **DAT** (**RNDM**(3,1)=1), there are no subject variables; as no nesting is required for  $V_1$  (**RNDM**(4,1)=0). The last element in this column is ignored.

The second column, (1,0,2,1,3), indicates one random variable (**RNDM**(1,2) = 1), no intercept (**RNDM**(2,2) = 0), the random variable is in the second column of **DAT** (**RNDM**(3,2) = 2), there is one subject variable (**RNDM**(4,2) = 1), and the subject variable is in the third column of **dat** (**RNDM**(5,2) = 3).

The corresponding Z matrix would have 14 columns, with 2 coming from  $V_1$  and 12 (4 × 3) from  $V_2$  nested within  $V_3$ . The, symmetric,  $Z^TZ$  matrix has the form

where 0 indicates a structural zero, i.e., it always takes the value 0, irrespective of the data, and - a value that is not a structural zero. The first two rows and columns of  $Z^TZ$  correspond to  $V_1$ . The block diagonal matrix in the 12 rows and columns in the bottom right correspond to  $V_2$  nested within  $V_3$ . With the 4 × 4 blocks corresponding to the levels of  $V_2$ . There are three blocks as the subject variable ( $V_3$ ) has three levels.

The model fitting functions, nag\_reml\_hier\_mixed\_regsn (g02jdc) and nag\_ml\_hier\_mixed\_regsn (g02jec), use the sweep algorithm to calculate the log likelihood function for a given set of variance

components. This algorithm consists of moving down the diagonal elements (called pivots) of a matrix which is similar in structure to  $Z^TZ$ , and updating each element in that matrix. When using the k diagonal element of a matrix A, an element  $a_{ij}, i \neq k, j \neq k$ , is adjusted by an amount equal to  $a_{ik}a_{ij}/a_{kk}$ . This process can be referred to as sweeping on the kth pivot. As there are no structural zeros in the first row or column of the above  $Z^TZ$ , sweeping on the first pivot of  $Z^TZ$  would alter each element of the matrix and therefore destroy the structural zeros, i.e., we could no longer guarantee they would be zero.

Reordering the RNDM matrix to

$$\mathbf{RNDM} = \begin{pmatrix} 1 & 1 \\ 0 & 0 \\ 2 & 1 \\ 1 & 0 \\ 3 & 0 \end{pmatrix}$$

i.e., the swapping the two columns, results in a  $Z^TZ$  matrix of the form

This matrix is identical to the previous one, except the first two rows and columns have become the last two rows and columns. Sweeping a matrix,  $A = \{a_{ij}\}$ , of this form on the first pivot will only affect those elements  $a_{ij}$ , where  $a_{i1} \neq 0$  and  $a_{1j} \neq 0$ , which is only the 13th and 14th row and columns, and the top left hand block of 4 rows and columns. The block diagonal nature of the first 12 rows and columns therefore greatly reduces the amount of work the algorithm needs to perform.

nag\_hier\_mixed\_init (g02jcc) constructs the  $Z^TZ$  as specified by the **RNDM** matrix, and does not attempt to reorder it to improve performance. Therefore for best performance some thought is required on what ordering to use. In general it is more efficient to structure **RNDM** in such a way that the first row relates to the deepest level of nesting, the second to the next level, etc..

## 10 Example

See Section 10 in nag reml hier mixed regsn (g02jdc) and nag ml hier mixed regsn (g02jec).

g02jcc.10 (last) Mark 24